



4-Channel Power Amplifier (Phone Jack MIC Input)

T-4S120



Specifications

Model	T-4S120
Rated Power Output	4x120W
Speaker Outputs	70V, 100V & 4~16Ω
Input Sensitivity & Impedance	775mV/10KΩ, Balanced phone jack type
Overload Electromotive Force	>15dB
Frequency Response	50Hz~16KHz (+1dB, -3dB)
S/N Ratio	>90dB
THD	Less than 0.5% at 1KHz, 1/3 rated power
Crosstalk	<50dB
Cooling	Fan automatically start up when temp reaches 55℃
Protection	Over heat, over load, clip & short circuit
Power Supply	~110V-230V 50/60Hz
Power Consumption	720W
Weight	21.86Kg
Dimensions	484 x 448 x 88mm
Finish	Panel: aluminum plate, black Case: SPCC Panel

Description

The 4 channel power amplifiers are designed for commercial and industrial public address applications. With four separate amplifier in a single chassis and rated power ranges from 60W, 120W and 240W per channel which provides a wide selection to meet different size sound system needs. The amplifier is design of rack mount type and T-4S60/T-4S120 are in 2U height while T-4S240 is in 3U height. Balanced line inputs by phone jack, 70V, 100V and 4-16Ω speaker outputs for each channel by phoenix types are convenient for installation when selection different speaker matching. Master volume controls for each control are included. Complete protection includes over heat, over load, clip & short circuit. Indications for power, signal, peak and protection.

Features

- * 4 separate amplifier into one chassis.
- * Rack mount amplifier in 2U(T-4S60/T-4S120) and 3U(T-4S240) types.
- * Rated power from 60W, 120W to 240W per channel.
- * 70V, 100V and 4-16Ω speaker outputs for each channel by phoenix types.
- * Isolated transformer for human safety operation.
- * Balanced phone jack type line input for each channel.
- * Reliable protection of over heat, over load, clip & short circuit.
- * Indications for power, signal, peak, and protection.
- * Excellent device of radiator cooling fan that ensures working effectively.

Rear Panel

